

George E. Antoniou

Transfer function computation for 3-D discrete systems

*Kybernetika*, Vol. 36 (2000), No. 5, [539]--547

Persistent URL: <http://dml.cz/dmlcz/135370>

## Terms of use:

© Institute of Information Theory and Automation AS CR, 2000

Institute of Mathematics of the Academy of Sciences of the Czech Republic provides access to digitized documents strictly for personal use. Each copy of any part of this document must contain these

*Terms of use.*



This paper has been digitized, optimized for electronic delivery and stamped with digital signature within the project *DML-CZ: The Czech Digital Mathematics Library*  
<http://project.dml.cz>

## TRANSFER FUNCTION COMPUTATION FOR 3-D DISCRETE SYSTEMS<sup>1</sup>

GEORGE E. ANTONIOU

A theoretically attractive and computationally fast algorithm is presented for the determination of the coefficients of the determinantal polynomial and the coefficients of the adjoint polynomial matrix of a given three-dimensional (3-D) state space model of Fornasini–Marchesini type. The algorithm uses the discrete Fourier transform (DFT) and can be easily implemented on a digital computer.

### 1. INTRODUCTION

During the past two decades there has been extensive research in multidimensional systems. This is due to the extensive range of applications, especially in signal and image processing, geophysics etc., [2, 4, 5]. State space techniques play a very important role in the analysis and synthesis of systems with more than one dimension. An interesting theoretical problem is to determine the coefficients of a transfer function from its state space representation and vice versa. In going from the transfer function to state space model a number of algorithms have been proposed [10]. In the case where a two-dimensional (2-D) state space model is available the Leverrier, Vandermode matrices or the DFT algorithms can be used to determine the transfer function coefficients [7, 11]. The DFT has been used for the evaluation of the transfer functions for one-dimensional regular [6, 9] and singular systems [1].

In this paper a computer implementable algorithm is proposed, using the DFT, for the computation of the 3-D transfer function for the Fornasini–Marchesini 3-D state space models. The proposed algorithm determines the coefficients of the determinantal polynomial and the coefficients of the adjoint polynomial matrix, using the DFT algorithm. The computational speed of the method could be improved using the fast Fourier transform (FFT).

Three-dimensional (3-D) state space models of the Fornasini–Marchesini type have the following structures [3]:

---

<sup>1</sup>This work was supported by the Margaret and Herman Sokol Faculty Award and the Faculty Scholarship Incentive Program of MSU/CS.

**First F–M model**

$$\begin{aligned}
 x(i_1 + 1, i_2 + 1, i_3 + 1) &= \mathbf{A}_1 x(i_1 + 1, i_2, i_3) + \mathbf{A}_2 x(i_1, i_2 + 1, i_3) \\
 &\quad + \mathbf{A}_3 x(i_1, i_2, i_3 + 1) + \mathbf{b}u(i_1, i_2, i_3) \\
 y(i_1, i_2, i_3) &= \mathbf{c}'x(i_1, i_2, i_3).
 \end{aligned}
 \tag{1}$$

**Second F–M model**

$$\begin{aligned}
 x(i_1 + 1, i_2 + 1, i_3 + 1) &= \mathbf{A}_1 x(i_1 + 1, i_2, i_3) + \mathbf{A}_2 x(i_1, i_2 + 1, i_3) \\
 &\quad + \mathbf{A}_3 x(i_1, i_2, i_3 + 1) + \mathbf{b}_1 u(i_1 + 1, i_2, i_3) \\
 &\quad + \mathbf{b}_2 u(i_1, i_2 + 1, i_3) + \mathbf{b}_3 u(i_1, i_2, i_3 + 1) \\
 y(i_1, i_2, i_3) &= \mathbf{c}'x(i_1, i_2, i_3)
 \end{aligned}
 \tag{2}$$

where,  $x(i_1, i_2, i_3) \in \mathcal{R}^n$ ,  $u(i_1, i_2, i_3) \in \mathcal{R}^m$ ,  $y(i_1, i_2, i_3) \in \mathcal{R}^p$ ,  $\mathbf{A}_k, \mathbf{b}, \mathbf{b}_k$  for  $k = 1, 2, 3$  and  $\mathbf{c}'$ , are real matrices of appropriate dimensions.

Applying the 3–D  $z_i$ , ( $\forall i = 1, 2, 3$ ) transform to the systems (1) and (2), with zero initial conditions, their transfer functions respectively become:

$$T_1(z_1, z_2, z_3) = \mathbf{c}' [\mathbf{I}z_1 z_2 z_3 - \mathbf{A}_1 z_1 - \mathbf{A}_2 z_2 - \mathbf{A}_3 z_3]^{-1} \mathbf{b}
 \tag{3}$$

and

$$T_2(z_1, z_2, z_3) = \mathbf{c}' [\mathbf{I}z_1 z_2 z_3 - \mathbf{A}_1 z_1 - \mathbf{A}_2 z_2 - \mathbf{A}_3 z_3] \times (b_1 z_1 + b_2 z_2 + b_3 z_3).
 \tag{4}$$

In the following section an interpolative approach is developed for determining the transfer function  $T(z_1, z_2, z_3)$ , given the matrices  $\mathbf{A}_k, \mathbf{b}, \mathbf{b}_k$  for  $k = 1, 2, 3$  and  $\mathbf{c}'$ , using the DFT. For the sake of completeness a brief description of the DFT follows.

**2. 3–D DFT**

Consider the finite sequences  $X(k_1, k_2, k_3)$  and  $\tilde{X}(r_1, r_2, r_3)$ ,  $k_i, \lambda_i = 0, \dots, M_i, \forall i = 1, 2, 3$ . In order for the sequences  $X(k_1, k_2, k_3)$  and  $\tilde{X}(r_1, r_2, r_3)$ , to constitute a 3–D DFT pair the following relations should hold [8]:

$$\tilde{X}(r_1, r_2, r_3) = \sum_{k_1=0}^{M_1} \sum_{k_2=0}^{M_2} \sum_{k_3=0}^{M_3} X(k_1, k_2, k_3) \times W_1^{-k_1 r_1} W_2^{-k_2 r_2} W_3^{-k_3 r_3}
 \tag{5}$$

$$X(k_1, k_2, k_3) = \frac{1}{R} \sum_{r_1=0}^{M_1} \sum_{r_2=0}^{M_2} \sum_{r_3=0}^{M_3} \tilde{X}(r_1, r_2, r_3) \times W_1^{k_1 r_1} W_2^{k_2 r_2} W_3^{k_3 r_3}
 \tag{6}$$

where,

$$R = \prod_{i=1}^3 (M_i + 1)
 \tag{7}$$

$$W_i = e^{(2\pi j)/(M_i+1)}, \forall i = 1, 2, 3
 \tag{8}$$

$X, \tilde{X}$  are discrete argument matrix valued functions, with dimensions  $p \times m$ .

### 3. FIRST F-M: DFT BASED ALGORITHM

The transfer function of the first Fornasini–Marchesini 3-D state space model (1) has the structure,

$$T(z_1, z_2, z_3) = \frac{N(z_1, z_2, z_3)}{d(z_1, z_2, z_3)} \tag{9}$$

where,

$$N(z_1, z_2, z_3) = \mathbf{c}' \text{ adj } [\mathbf{I}z_1z_2z_3 - \mathbf{A}_1z_1 - \mathbf{A}_2z_2 - \mathbf{A}_3z_3]\mathbf{b} \tag{10}$$

$$d(z_1, z_2, z_3) = \det [\mathbf{I}z_1z_2z_3 - \mathbf{A}_1z_1 - \mathbf{A}_2z_2 - \mathbf{A}_3z_3]. \tag{11}$$

Taking into consideration that

$$\begin{aligned} n &= \text{deg}_{z_1}[N(z_1, z_2, z_3)] = \text{deg}_{z_2}[N(z_1, z_2, z_3)] \\ &= \text{deg}_{z_3}[N(z_1, z_2, z_3)] \end{aligned}$$

and

$$\begin{aligned} n &= \text{deg}_{z_1}[d(z_1, z_2, z_3)] = \text{deg}_{z_2}[d(z_1, z_2, z_3)] \\ &= \text{deg}_{z_3}[d(z_1, z_2, z_3)] \end{aligned}$$

where,  $\text{deg}_{z_1}[\ ]$ ,  $\text{deg}_{z_2}[\ ]$ ,  $\text{deg}_{z_3}[\ ]$  denote the degrees with respect to  $z_1, z_2$ , and  $z_3$ , respectively. Equations (10) and (11) can be written in polynomial form as follows:

$$N(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n \mathbf{P}_{\kappa,\lambda,\mu} z_1^\kappa z_2^\lambda z_3^\mu \tag{12}$$

$$d(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa,\lambda,\mu} z_1^\kappa z_2^\lambda z_3^\mu \tag{13}$$

where,  $P_{\kappa,\lambda,\mu}$  are matrices with dimensions  $(p \times m)$ , while  $q_{\kappa,\lambda,\mu}$  are scalars.

The numerator polynomial matrix  $N(z_1, z_2, z_3)$  and the denominator polynomial  $d(z_1, z_2, z_3)$  can be numerically computed at  $R = \prod_{i=1}^3 (M_i + 1)$ , points, equally spaced on the unit 3 – D space. The  $R$  points are chosen as

$$W_i = W = e^{(2\pi j)/(M_i+1)}, \quad \forall i = 1, 2, 3. \tag{14}$$

The values of the transfer function (9) at the  $R$  points are its corresponding 3-D DFT coefficients.

Moreover, we define

$$v_1(r) = v_2(r) = v_3(r) = W^r, \quad \forall r = 0, \dots, n \tag{15}$$

#### 3.1. Denominator polynomial

To evaluate the denominator coefficients  $q_{\kappa,\lambda,\mu}$ , define,

$$a_{i_1, i_2, i_3} = \det [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1v_1(i_1) - \mathbf{A}_2v_2(i_2) - \mathbf{A}_3v_3(i_3)]. \tag{16}$$

Therefore using equations (13), (16) yield

$$a_{i_1, i_2, i_3} = d[v_1(i_1), v_2(i_2), v_3(i_3)]. \tag{17}$$

Provided that at least one of  $a_{i_1, i_2, i_3} \neq 0$ .

Equations (13), (15) and (17) yield

$$a_{i_1, i_2, i_3} = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} W^{-(i_1 \kappa + i_2 \lambda + i_3 \mu)}. \tag{18}$$

Using equations (18) and (5) it is obvious that,  $[a_{i_1, i_2, i_3}]$  and  $[q_{\kappa, \lambda, \mu}]$  form a DFT pair. Therefore the coefficients  $q_{\kappa, \lambda, \mu}$  can be computed, using the inverse 3-D DFT, as follows:

$$q_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n a_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)} \tag{19}$$

where,  $\kappa, \lambda, \mu = 0, \dots, n$ .

### 3.2. Numerator polynomial

To evaluate the numerator matrix polynomial  $\mathbf{P}_{\kappa, \lambda, \mu}$ , define

$$\mathbf{F}_{i_1, i_2, i_3} = c' \text{ adj } [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1v_1(i_1) - \mathbf{A}_2v_2(i_2) - \mathbf{A}_3v_3(i_3)] \mathbf{b}. \tag{20}$$

Provided that at least one of  $\mathbf{F}_{i_1, i_2, i_3} \neq 0$ .

Therefore using equations (10),(20), yields

$$\mathbf{F}_{i_1, i_2, i_3} = \mathbf{N}[v_1(i_1), v_2(i_2), v_3(i_3)]. \tag{21}$$

Equations (12), (15) and (21) yield

$$\mathbf{F}_{i_1, i_2, i_3} = \sum_{k=0}^n \sum_{r=0}^n \sum_{r=0}^n \mathbf{P}_{\kappa, \lambda, \mu} W^{-(i_1 \kappa + i_2 \lambda + i_3 \mu)}. \tag{22}$$

Using equations (19) and (5) it is obvious that,  $[\mathbf{F}_{i_1, i_2, i_3}]$  and  $[P_{\kappa, \lambda, \mu}]$  form a DFT pair. Therefore the coefficients  $P_{\kappa, \lambda, \mu}$  can be computed, using the inverse 3-D DFT, as follows:

$$\mathbf{P}_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n \mathbf{F}_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)} \tag{23}$$

where,  $\kappa, \lambda, \mu = 0, \dots, n$ .

Finally, the transfer function sought is,

$$T(z_1, z_2, z_3) = \frac{N(z_1, z_2, z_3)}{d(z_1, z_2, z_3)} \tag{24}$$

where,

$$N(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n P_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu \tag{25}$$

$$d(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu. \tag{26}$$

A synopsis of the proposed algorithm is depicted in Table 1.

Table 1

let

$$n = \dim(\mathbf{I}) = \dim(\mathbf{A}_1) = \dim(\mathbf{A}_2) = \dim(\mathbf{A}_3)$$

$$W_i = e^{(2\pi j)/(M_i+1)}, \quad \forall i = 1, 2, 3$$

for  $r = 0$  to  $n$  do

let

$$v_1(r) = v_2(r) = v_3(r) = W^r, \quad \forall r = 0, \dots, n$$

for  $i_1 = 0$  to  $n$  do

for  $i_2 = 0$  to  $n$  do

for  $i_3 = 0$  to  $n$  do

compute

$$a_{i_1, i_2, i_3} = \det [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1 v_1(i_1) - \mathbf{A}_2 v_2(i_2) - \mathbf{A}_3 v_3(i_3)]$$

$$\mathbf{F}_{i_1, i_2, i_3} = \mathbf{c}' \text{adj} [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1 v_1(i_1) - \mathbf{A}_2 v_2(i_2) - \mathbf{A}_3 v_3(i_3)]\mathbf{b}$$

end for

end for

for  $i_1 = 0$  to  $n$  do

for  $i_2 = 0$  to  $n$  do

for  $i_3 = 0$  to  $n$  do

compute

$$q_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n a_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)}$$

$$P_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n \mathbf{F}_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)}$$

end for

end for

then

$$T(z_1, z_2, z_3) = \frac{N(z_1, z_2, z_3)}{d(z_1, z_2, z_3)} = \frac{\sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n P_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu}{\sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu}$$

#### 4. SECOND F-M: DFT BASED ALGORITHM

The transfer function of the second Fornasini–Marchesini 3-D state space model has the structure,

$$T(z_1, z_2, z_3) = \frac{N(z_1, z_2, z_3)}{d(z_1, z_2, z_3)} \quad (27)$$

where,

$$N(z_1, z_2, z_3) = \mathbf{c}' \text{adj} [\mathbf{I}z_1z_2z_3 - \mathbf{A}_1z_1 - \mathbf{A}_2z_2 - \mathbf{A}_3z_3] \times (\mathbf{b}_1z_1 + \mathbf{b}_2z_2 + \mathbf{b}_3z_3) \quad (28)$$

$$d(z_1, z_2, z_3) = \det [\mathbf{I}z_1z_2z_3 - \mathbf{A}_1z_1 - \mathbf{A}_2z_2 - \mathbf{A}_3z_3]. \quad (29)$$

Taking into consideration that

$$\begin{aligned} n &= \deg_{z_1}[N(z_1, z_2, z_3)] = \deg_{z_2}[N(z_1, z_2, z_3)] \\ &= \deg_{z_3}[N(z_1, z_2, z_3)] \end{aligned}$$

and

$$\begin{aligned} n &= \deg_{z_1}[d(z_1, z_2, z_3)] = \deg_{z_2}[d(z_1, z_2, z_3)] \\ &= \deg_{z_3}[d(z_1, z_2, z_3)] \end{aligned}$$

where,  $\deg_{z_1}[\ ]$ ,  $\deg_{z_2}[\ ]$ ,  $\deg_{z_3}[\ ]$  denote the degrees with respect to  $z_1$ ,  $z_2$ , and  $z_3$ , respectively. Equations (28) and (29) can be written in polynomial form as follows:

$$N(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n \mathbf{P}_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu \quad (30)$$

$$d(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu \quad (31)$$

where,  $P_{\kappa, \lambda, \mu}$  are matrices with dimensions  $(p \times m)$ , while  $q_{\kappa, \lambda, \mu}$  are scalars.

The numerator polynomial matrix  $N(z_1, z_2, z_3)$  and the denominator polynomial  $d(z_1, z_2, z_3)$  can be numerically computed at  $R = \prod_{i=1}^3 (M_i + 1)$  points, equally spaced on the unit 3-D space. The  $R$  points are chosen as

$$W_i = W = e^{(2\pi j)/(M_i+1)}, \quad \forall i = 1, 2, 3. \quad (32)$$

The values of the transfer function (27) at the  $R$  points are its corresponding 3-D DFT coefficients.

Moreover, we define

$$v_1(r) = v_2(r) = v_3(r) = W^r, \quad \forall r = 0, \dots, n. \quad (33)$$

##### 4.1. Denominator polynomial

To evaluate the denominator coefficients  $q_{\kappa, \lambda, \mu}$ , define,

$$a_{i_1, i_2, i_3} = \det [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1v_1(i_1) - \mathbf{A}_2v_2(i_2) - \mathbf{A}_3v_3(i_3)]. \quad (34)$$

Therefore using equations (5) and (34) yield

$$a_{i_1, i_2, i_3} = d[v_1(i_1), v_2(i_2), v_3(i_3)]. \tag{35}$$

Provided that at least one of  $a_{i_1, i_2, i_3} \neq 0$ .

Equations (31), (33) and (35) yield

$$a_{i_1, i_2, i_3} = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} W^{-(i_1 \kappa + i_2 \lambda + i_3 \mu)}. \tag{36}$$

Using equations (36) and (5) it is obvious that,  $[a_{i_1, i_2, i_3}]$  and  $[q_{\kappa, \lambda, \mu}]$  form a DFT pair. Therefore the coefficients  $q_{\kappa, \lambda, \mu}$  can be computed, using the inverse 3-D DFT, as follows:

$$q_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n a_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)} \tag{37}$$

where,  $\kappa, \lambda, \mu = 0, \dots, n$ .

#### 4.2. Numerator polynomial

To evaluate the numerator matrix polynomial  $\mathbf{P}_{\kappa, \lambda, \mu}$ , define

$$\begin{aligned} \mathbf{F}_{i_1, i_2, i_3} &= \mathbf{c}' \text{adj} [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1v_1(i_1) - \mathbf{A}_2v_2(i_2) - \mathbf{A}_3v_3(i_3)] \\ &\quad \times (\mathbf{b}_1v_1(i_1) + \mathbf{b}_2v_2(i_2) + \mathbf{b}_3v_3(i_3)). \end{aligned} \tag{38}$$

Provided that at least one of  $\mathbf{F}_{i_1, i_2, i_3} \neq 0$ .

Therefore using equations (5) and (38), yields

$$\mathbf{F}_{i_1, i_2, i_3} = \mathbf{N}[v_1(i_1), v_2(i_2), v_3(i_3)]. \tag{39}$$

Equations (30), (33) and (39) yield

$$\mathbf{F}_{i_1, i_2, i_3} = \sum_{k=0}^n \sum_{r=0}^n \sum_{r=0}^n \mathbf{P}_{\kappa, \lambda, \mu} W^{-(i_1 \kappa + i_2 \lambda + i_3 \mu)}. \tag{40}$$

Using equations (40) and (5) it is obvious that,  $[a_{i_1, i_2, i_3}]$  and  $[q_{\kappa, \lambda, \mu}]$  form a DFT pair. Therefore the coefficients  $q_{\kappa, \lambda, \mu}$  can be computed, using the inverse 3-D DFT, as follows:

$$\mathbf{P}_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n \mathbf{F}_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)} \tag{41}$$

where,  $\kappa, \lambda, \mu = 0, \dots, n$ .

Finally, the transfer function sought is,

$$T(z_1, z_2, z_3) = \frac{N(z_1, z_2, z_3)}{d(z_1, z_2, z_3)} \tag{42}$$

where,



$$N(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n P_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu \tag{43}$$

$$d(z_1, z_2, z_3) = \sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu. \tag{44}$$

A synopsis of the proposed algorithm is depicted in Table 2.

**Table 2**

let

$$n = \dim(\mathbf{I}) = \dim(\mathbf{A}_1) = \dim(\mathbf{A}_2) = \dim(\mathbf{A}_3)$$

$$W_i = e^{(2\pi j)/(M_i+1)}, \quad \forall i = 1, 2, 3$$

for  $r = 0$  to  $n$  do  
  let

$$v_1(r) = v_2(r) = v_3(r) = W^r, \quad \forall r = 0, \dots, n$$

for  $i_1 = 0$  to  $n$  do  
for  $i_2 = 0$  to  $n$  do  
for  $i_3 = 0$  to  $n$  do  
  compute

$$a_{i_1, i_2, i_3} = \det [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1 v_1(i_1) - \mathbf{A}_2 v_2(i_2) - \mathbf{A}_3 v_3(i_3)]$$

$$F_{i_1, i_2, i_3} = c' \text{adj} [\mathbf{I}v_1(i_1)v_2(i_2)v_3(i_3) - \mathbf{A}_1 v_1(i_1) - \mathbf{A}_2 v_2(i_2) - \mathbf{A}_3 v_3(i_3)]$$

$$\times (\mathbf{b}_1 v_1(i_1) + \mathbf{b}_2 v_2(i_2) + \mathbf{b}_3 v_3(i_3))$$

end for  
end for  
for  $i_1 = 0$  to  $n$  do  
for  $i_2 = 0$  to  $n$  do  
for  $i_3 = 0$  to  $n$  do  
  compute

$$q_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n a_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)}$$

$$P_{\kappa, \lambda, \mu} = \frac{1}{R} \sum_{i_1=0}^n \sum_{i_2=0}^n \sum_{i_3=0}^n F_{i_1, i_2, i_3} W^{(i_1 \kappa + i_2 \lambda + i_3 \mu)}$$

end for  
end for  
then

$$T(z_1, z_2, z_3) = \frac{N(z_1, z_2, z_3)}{d(z_1, z_2, z_3)} = \frac{\sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n P_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu}{\sum_{\kappa=0}^n \sum_{\lambda=0}^n \sum_{\mu=0}^n q_{\kappa, \lambda, \mu} z_1^\kappa z_2^\lambda z_3^\mu}$$

## 5. CONCLUSION

In this paper the well known DFT algorithm has been used for determining the coefficients of a 3-D transfer function from its 3-D state space of Fornasini-Marchesini type. The algorithms are theoretically straight forward and can be easily implemented. The results presented here can be extended to multidimensional case.

(Received September 24, 1999.)

## REFERENCES

- [1] G. E. Antoniou, G. O. A. Glentis, S. J. Varoufakis and D. A. Karras: Transfer function determination of singular systems using the DFT. *IEEE Trans. Circuits and Systems CAS-36* (1989), 1140-1142.
- [2] N. K. Bose: *Applied Multidimensional Systems*. Van Nostrand, Reinhold, 1982.
- [3] E. Fornasini and E. Marchesini: Doubly indexed dynamical systems: state space models and structural properties. *Math. Systems Theory* 12 (1978), 1, 59-72.
- [4] K. Galkowski: *State Space Realizations on n-D Systems*. Monograph No. 76, Wroclaw Technical University, Wroclaw 1994.
- [5] T. Kaczorek: *Two dimensional linear systems*. (Lecture Notes in Control and Informations Sciences 68.) Springer-Verlag, Berlin 1985.
- [6] T. Lee: A simple method to determine the characteristic function  $f(s) = |sI - A|$  by discrete Fourier series and fast Fourier transform. *IEEE Trans. Circuits and Systems CAS-35* (1976), 3, 242.
- [7] H. Luo, W.-S. Lu and A. Antoniou: New algorithms for the derivation of the transfer-function matrices of 2-D state-space discrete systems. I: Fundamental theory and applications. *IEEE Trans. Circuits and Systems CAS-44* (1997), 2, 112-119.
- [8] A. V. Oppenheim and R. W. Schaefer: *Digital Signal Processing*. Prentice-Hall, Englewood Cliffs, N. J. 1975.
- [9] L. E. Paccagnella et al: FFT calculation of a determinantal polynomial. *IEEE Trans. Automat. Control AC-21* (1976), 401.
- [10] P. N. Paraskevopoulos, S. J. Varoufakis and G. E. Antoniou: Minimal state space realization of 3-D systems. *IEE Proceedings Part G* 135 (1988), 65-70.
- [11] K. S. Yeung and F. Kumbi: Symbolic matrix inversion with application to electronic circuits. *IEEE Trans. Circuits and Systems CAS-35* (1988), 2, 235-239.

*Prof. Dr. George E. Antoniou, Image Processing and Systems Laboratory, Department of Computer Science, Montclair State University, Upper Montclair, New Jersey 07043. U. S. A.*

*e-mail: george.antoniou@montclair.edu*